

P4 – Subscriber Monitoring


The P4 telephone has the ability to monitor the status of up to 8 extensions, and show if the phones are in use.

Straight out of the box, the P4 telephone is configured to monitor the following extensions:

11	12	13	14	21	22	31	32
----	----	----	----	----	----	----	----

However, these are not always the extensions that you would wish to observe.

To change the extensions, you need to access the “EURACOM MONITORING” menu, which is accessed by the following key sequence:



From within that menu item, use the up/down arrows to go to “SUBSCRIBER MONITOR”, and select it by pressing “2”



Eight “SUBS” will now be available, via the up and down keys. These correspond to the eight positions on the screen, with “SUBS 1” being the left position, through to “SUBS 8” as the right-hand position. Using the up-down keys, move the selection to the required “SUBS” number, and press the corresponding number key for that position.

11	12	13	14	21	22	31	32
SUBS 1	SUBS 2	SUBS 3	SUBS 4	SUBS 5	SUBS 6	SUBS 7	SUBS 8

Delete any unwanted digits from the currently selected extension, using the down key



Use the number keys to enter the new extension you require to be displayed, then accept this change with the programming key

